

Checking the **Supplied Accessories**

Along with your new LCD projection TV, the packing box contains a remote control and two AA (R6) batteries. These items are all you need to set up and use the TV.

Connecting Your TV


• Review the following chart to determine which diagram to use to connect the components in your system:

For these	componer	nts			See reverse side
Cable/Antenna	Cable Box Of	Satellite Receiver	o o vcr	Sony Dream System	A
Cable/Antenna	Cable Box Of	Satellite Receiver	o o vcr	DVD Player	В
Cable/Antenna	Cable Box Of	Satellite Receiver	o o vcr	DVD Player AV F	Receiver
Cable/Antenna	Cable Box	o o vcr	DVD Player	Satellite Receiver	D
Cable/Antenna Digital Recorder	Cable Box Of	Satellite Receiver	o o vcr	Player AV F	Receiver
Cable/Antenna	HD Cable Box	o o ver	DVD Player		F

- See the "Cables Required" chart that appears with the diagram to determine which cables you'll need. You may need to purchase extra accessories, such as cables and splitters, depending on the components you plan to connect.
- Turn off and unplug all components before making connections.
- If you are connecting a digital cable box, you'll need a special bidirectional splitter that's compatible with your cable box. Contact your cable provider for details.

Making Video Connections

Your TV includes several types of video inputs. Use the inputs that are available on your components that provide the best video performance, as described in right.




Additional Connections

For best audio performance, connect your digital audio components using either digital optical or digital coaxial audio connections. Depending on which components are in your system, you may need to complete additional connections. For example, if you have a satellite receiver, you'll need to connect the satellite antenna. If you have an A/V receiver, you'll need to connect speakers.

The connection diagrams shown in the reverse side are recommendations only; other possible solutions may exist. Connections that include an A/V receiver can often be very complex, so check your A/V receiver's instruction manual for additional details.

Activating CableCARD™ Service

Before you can use CableCARD service, you need to insert the CableCARD (supplied by your cable provider) and activate the service, as described in right.



Inserting the CableCARD incorrectly may result in permanent damage to the card and

Running Initial Setup

- **1** Press POWER to turn on the TV. The Initial Setup screen appears.
- 2 Press **★**/**♦** to select the on-screen display language. Then press

The message "Start auto program now?" appears.

3 Press **♦**/**♦** to select "Yes", then press (+) only.

Initial Setup automatically creates a list of receivable channels. When finished, the lowest numbered channel is displayed

If you need to perform Auto Program again

- 1 Press MENU.
- 2 Press **♦**/**♦** to select 🖶 (Channel), then press ⊕.
- 3 Press **↑**/**♦** to select "Auto Program," then press ⊕.
- 4 Press (+).

"Auto Program" appears and the TV starts scanning and presetting channels automatically. When all the receivable channels are stored, the "Show/Hide Channels" menu appears. Using this menu, you can start skipping unwanted channels (see "Selecting Channel Options" in the operating instructions).

- **5** Press MENU to exit the menu screen.
- Auto Program may take up to 50 minutes to complete. A progress bar will display the approximate progress of the Auto Program and Digital Channels/Add sequences.

Programming the Remote Control


The remote control is preset to operate Sony brand video equipment.

Sony Equipment	Programmable Code Number
DVD/VCR	601 (Sony Dream System)
SAT/Cable	801 (Sony Satellite Receiver)

If you have video equipment other than Sony brand that you want to control with the LCD projection TV's remote control, use the following procedures to program the remote control.

The equipment must have infrared (IR) remote capability in order to be used with this

Using the code list below, find the three-digit code number for the manufacturer of your equipment. (If more than one code number is listed, use the number listed first.)



- 1 Press the DVD/VCR (FUNCTION) and RESET buttons simultaneously, or press the SAT/CABLE (FUNCTION) and RESET buttons simultaneously. DVD/VCR and SAT/CABLE buttons flash.
- **2** Press the function button you want to program. To program a cable box or a satellite receiver Press SAT/CABLE (FUNCTION).

To program video equipment Press DVD/VCR (FUNCTION).

- -1, 2 3 Enter the three-digit manufacturer's code number using the 0-9 buttons.
 - 4 Press ENT (enter).
 - 5 To check if the code number works, aim the TV's remote control at the equipment and press DVD/ VCR and/or SAT/CABLE (POWER) that corresponds with that equipment. If it responds, the programming is completed. If not, try using the other codes listed for that manufacturer.
- 🖾 If more than one code number is listed, try entering them one by one until you come to the correct code for your equipment.
- If you enter a new code number, the code number you previously entered at that setting is erased.

322, 313, 321

330, 335

Signature 2000 (M.Ward) 338, 327

SV 2000

In some cases, you may not be able to operate your equipment with the supplied remote control. In such cases, use the equipment's own remote control unit.

Manufacturer's codes Manufacturer Code 319. 317 **DVD Players** 309, 308 Manufacturer Code 304, 338, 309 341, 312, 309 314, 336, 337 319, 320, 316, 317, 318, 341 330, 335 Funai 338 General Electric 329, 304, 309 309, 308 309, 305, 304, 330, 314, 336, 337 **DVD Changers** Manufacturer Code 314, 336, 337, 345 314, 336, 332, 337 LXI (SEARS) 332, 305, 330, 335 **DVD/VCR Combo Units** Manufacturer Code 308, 309, 310 Marantz 314, 336, 337 Marta 332 Memorex 309, 335 Minolta 305, 304 323, 324, 325, 326 773 314, 336, 337 768 309, 308 Olympic **HDD/DVD Combo Units** 317 Manufacturer Code 308, 309, 306, 307 770, 771, 772 5.1ch DVD AV System 308, 309, 310 Manufacturer Code Sony (DAV) 601, 602, 603, 604 Quasar 308, 309, 306 304, 305, 308, 309, 311, 312, 313, 310, **AV Receivers** Manufacturer Code 309, 330, 328, 335, 324, 338

VCRs

Manufacturer Code

Admiral (M. Ward) 327

301, 302, 303

338, 344

314, 337

Technics Toshiba Wards Yamaha Zenith Cable Boxes	332
Wards Yamaha Zenith	327, 328, 335, 33 332 314, 330, 336, 33
Yamaha Zenith	332 314, 330, 336, 33
Zenith	
	331
Cable Boxes	
Manufacturer	Code
Sony	230
Hamlin/Regal	222, 223, 224, 22 226
Jerrold/G.I./Motorola	201, 202, 203, 20 205, 206, 207, 20 218, 222
Oak	227, 228, 229
Panasonic	219, 220, 221
Pioneer	214, 215
	209, 210, 211
Scientific Atlanta	207, 210, 211
Scientific Atlanta Tocom	216, 217
Tocom Zenith	216, 217 212, 213
Tocom	216, 217 212, 213
Tocom Zenith Satellite Receive Manufacturer Sony	216, 217 212, 213 vers
Tocom Zenith Satellite Recei Manufacturer	216, 217 212, 213 vers Code
Tocom Zenith Satellite Receiv Manufacturer Sony Dish Network Echostar	216, 217 212, 213 vers Code 801
Tocom Zenith Satellite Recei Manufacturer Sony Dish Network Echostar General Electric	216, 217 212, 213 Vers Code 801 810 810 802
Tocom Zenith Satellite Receiv Manufacturer Sony Dish Network Echostar	216, 217 212, 213 Vers Code 801 810 810
Tocom Zenith Satellite Recei Manufacturer Sony Dish Network Echostar General Electric Hitachi Hughes	216, 217 212, 213 Vers Code 801 810 810 802 805 804
Tocom Zenith Satellite Recei Manufacturer Sony Dish Network Echostar General Electric Hitachi Hughes Mitsubishi	216, 217 212, 213 Vers Code 801 810 810 802 805
Tocom Zenith Satellite Receive Manufacturer Sony Dish Network Echostar General Electric Hitachi Hughes Mitsubishi Panasonic	216, 217 212, 213 Vers Code 801 810 802 805 804 809 803
Tocom Zenith Satellite Recei Manufacturer Sony Dish Network Echostar General Electric Hitachi Hughes Mitsubishi	216, 217 212, 213 Vers Code 801 810 802 805 804 809

Manufacturer Code

308, 309, 338, 310

338


Replacing the Lamp

If the screen becomes dark, the color looks unusual, or the LAMP indicator on the front of the LCD projection TV flashes, it is time to replace the lamp with a new one (not supplied).

- Luse a Sony XL-2100U or XL-2100 (for WE655 series) or XL-2200 (for WF655 series) replacement lamp (not supplied) for replacement. Use of any other lamp may damage the
- D Before replacing the lamp, turn the power off on the main unit. Wait several minutes, then unplug the power cord. (The cooling fan will continue to blow for about two minutes after turning the power off.)
- 🖾 Allow the lamp to cool down completely before removing it. The surface of the lamp remains extremely hot for at least 30 minutes after the power has been turned off.

Sony XL-2100U or XL-2100 for KDF-WE655 series

- 1 Loosen the screws on the rear side panel.
- *The illustration described in right is for KDF-50WE655.
- **2** Remove the front panel.




- **3** Loosen the screw with a coin or similar object to remove the lamp cover.
- 4 Loosen the two screws that hold the lamp, then pull out the lamp.




- 5 Replace the new lamp and tighten the screws.
- **6** Reattach the lamp cover and tighten the screw.
- **7** Reattach the front panel securely.
- **8** Tightly screw the side panel in its place.


Sony XL-2200 for KDF-WF655 series/KDF-XS955 series

1 Loosen the screws on the rear side panel. (only for WF655)



2 Remove the front panel.





3 Loosen the screw, release the bar (for WF655) or slide the knob to left (for XS955), and remove the lamp cover.










4 Loosen the screw that secure the lamp, then pull out the lamp.









- **5** Replace the new lamp and tighten the screw.
- **6** Reattach the lamp cover and tighten the screw.
- 7 Reattach the front panel securely.
- **8** Tightly screw the side panel in its place. (only for WF655)

